



## Wire Less Lan Antenna

### C-621 Series



P/N	Frequency	Connector	Dimensions
C-621	880~960 & 1710~1880MHz	SMA Male (90°)	16.6 x 53.5 mm
C-621-2	850 & 1850~1990 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-621-4	824~960 & 1710~1990 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-621-7	418 MHz	SMA Male Reverse (90°)	16.6 x 53.5 mm
C-621-8	433 MHz	SMA Male Reverse (90°)	16.6 x 53.5 mm
C-621-9	315 MHz	SMA Male Reverse (90°)	16.6 x 53.5 mm
C-621-12	860~930 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-621-13	880~960 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-638	880~960 & 1710~1990 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-638-2	880~960 & 1710~1990 MHz	SMA Male Reverse (90°)	16.6 x 53.5 mm
C-638-3	824~896 & 1850~2025 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-761	890~960 & 1710~1880 MHz	FME Female(90°)	19.5 x 53.0 mm
C-786	880~960 & 1710~1880 MHz	SMA Male (Bcr)	11.0 x 53.2 mm
C-821	868 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-829-1	915 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-829-2	915 MHz	SMA Male Reverse (90°)	16.6 x 53.5 mm
C-845	315 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-846	433 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-850	405~415 MHz	SMA Male (90°)	16.6 x 53.5 mm
C-851	800~870 MHz	SMA Male (90°)	16.6 x 53.5 mm
S-022-1	2.4~2.5 GHz	SMA Male (90°)	16.6 x 53.5 mm
S-124	2.45 GHz	SMA Male Reverse (90°)	16.6 x 53.5 mm



C-621-10	880~960 & 1710~1880 MHz	FME Female	9.4 x 64.0 mm
C-621-11	890~960 & 1710~1990 MHz	FME Female	9.4 x 64.0 mm
C-605	880~960 & 1710~1880 MHz	MMCX Male	9.4 x 53.0 mm
C-605-2	890~960 & 1710~1990 MHz	MMCX Male	9.4 x 53.0 mm (White Tube)
C-688-1	890~960 & 1770~1990MHz	SMA Male	9.4 x 56.0 mm
C-688-2	824~894 & 1850~1990 MHz	SMA Male Reverse	9.4 x 56.0 mm
C-688-4	433 MHz	SMA Male	9.4 x 56.0 mm
C-813	824~960 MHz	SMA Male	9.4 x 56.0 mm
C-858	890~960 / 1710~1880 MHz	FME Female	9.7 x 56.2 mm
C-686-9	315 MHz	SMA Male	9.4 x 56.0 mm
S-031	2.4~2.5 GHz	SMA Male	9.4 x 56.0 mm
S-158	2.4~2.5 GHz	MMCX Male (RG-178x300mm)	9.4 x 45.0 mm